

Active Optical Cable QSFP28 to QSFP28, 100G, 1 to 25 Meter riser rated (OFNR), Coded for Various Platforms

AOC-Q28-ER-RRR-PPP



Features

- · Operating Data Rates up to 100G
- Distance Range from 1 Meter to 30 Meters (additional standard and custom lengths are available)
- Hot Pluggable QSFP28
- Simplifies Patching & Offers a Cost-effective approach for Short Links
- Standard Temperature Range (available in Industrial Operating Temperatures)
- 100% compatible with other OEM and third-party Active Optical Cables

Applications

- · Telecommunication Service Providers
- Metro Ethernet
- · Intra-rack and across rack interconnect
- · Transport Networks

- · Switch and router high speed
- backplane interconnect
- · High-performance computing clusters

Description

The L-com AOC-Q28-ER-RRR-PPP series is a 100G QSFP28 to QSFP28 Active Optical Cable, that is factory pre-programmed with all the necessary configuration data for seamless network integration and digital diagnostics for performance monitoring. The L-com AOC-Q28-ER-RRR-PPP Active Optical Cable series is designed, programmed and tested to perform identically to and is 100% compatible with other OEM and third-party Active Optical Cables. The L-com's AOC-Q28-ER-RRR-PPP Active Optical Cable series has been manufactured with riser rated (OFNR) cable in lengths from 1 meter to 30 meters (additional standard and custom lengths are available) of reach at a center wavelength of 850 nm. The L-com AOC-Q28-ER-RRR-PPP Active Optical Cable series is tested for 100% functionality and guaranteed compatible for outstanding network performance.

L-com offers all brands and form factors of Active Optical Cables, optical transceivers and cabling for all your networking needs. Now you have a reliable, compatible and affordable means to expand your network while maintaining its integrity. Contact our technical support and sales staff with your questions on fiber optic connectivity or other L-com products.

Configuration

Module Form Factor Maximum Data Rate Manufacturer Compatibility Distance Jacket Burn Rating QSFP28 100Gbps Various Platforms, See Table 1 to 3 m OFNR

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Center Wavelength		850		nm
Supply Voltage (VccT, VccR)	3.14	3.3	3.46	V
Supply Current (Icc)			750	mA
Transmitter Differential Input Swing (Vin,pp)			900	mVpp
Transmitter Input Voltage Tolerance (VinT) -0.3		4	V

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: AOC-Q28-ER-RRR-PPP



AOC-Q28-ER-RRR-PPP



Receiver Output Voltage -0.3 4 V

Environmental Specifications

Temperature

Operating Range 0C to 70C (Without air flow)

Storage Range -40C to 85C

Relative Humidity 5% to 95%

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:



AOC-Q28-ER-RRR-PPP



QSFP28 Pin Assignment & Pin Assignment Table

38	GND	
37	TX1n	
36	TX1p	
35	GND	
34	TX3n	
33	TX3p	
32	GND	
31	LPMode	
30	Vcc1	
29	VccTx	
28	IntL	
27	ModPrsL	
26	GND	
25	RX4p	
24	RX4n	
23	GND	
22	RX2p	
21	RX2n	
20	GND	

GND 2 TX2n 3 TX2p 4 5 GND TX4n 6 TX4p 7 GND ModSelL 8 9 ResetL VccRx 10 SCL 11 SDA 12 GND 13 RX3p 14 RX3n 15 GND 16 17 RX1p RX1n 18 GND 19

Top Side

Bottom Side

Pin out of Connector Block on Host Board

Card Edge



AOC-Q28-ER-RRR-PPP



Pin	Symbol	Name/Description	NOT
1	GND	Transmitter Ground (Common with Receiver Ground)	1
2	Tx2n	Transmitter Inverted Data Input	
3	Tx2p	Transmitter Non-Inverted Data output	
4	GND	Transmitter Ground (Common with Receiver Ground)	1
5	Tx4n	Transmitter Inverted Data Input	
6	Tx4p	Transmitter Non-Inverted Data output	
7	GND	Transmitter Ground (Common with Receiver Ground)	1
8	ModSelL	Module Select	
9	ResetL	Module Reset	
10	VccRx	3.3V Power Supply Receiver	2
11	SCL	2-Wire serial Interface Clock	
12	SDA	2-Wire serial Interface Data	
13	GND	Transmitter Ground (Common with Receiver Ground)	
14	Rx3p	Receiver Non-Inverted Data Output	
15	Rx3n	Receiver Inverted Data Output	
16	GND	Transmitter Ground (Common with Receiver Ground)	1
17	Rx1p	Receiver Non-Inverted Data Output	
18	Rx1n	Receiver Inverted Data Output	
19	GND	Transmitter Ground (Common with Receiver Ground)	1
20	GND	Transmitter Ground (Common with Receiver Ground)	1
21	Rx2n	Receiver Inverted Data Output	1
22	Rx2p	Receiver Non-Inverted Data Output	
23	GND	Transmitter Ground (Common with Receiver Ground)	1
24	Rx4n	Receiver Inverted Data Output	1
25	Rx4p	Receiver Non-Inverted Data Output	
26	GND	Transmitter Ground (Common with Receiver Ground)	1
27	ModPrsl	Module Present	
28	IntL	Interrupt	1
29	VccTx	3.3V power supply transmitter	2
30	Vcc1	3.3V power supply	2
31	LPMode	Low Power Mode, not connect	
32	GND	Transmitter Ground (Common with Receiver Ground)	1
33	Tx3p	Transmitter Non-Inverted Data Input	
34	Tx3n	Transmitter Inverted Data Output	
35	GND	Transmitter Ground (Common with Receiver Ground)	1
36	Tx1p	Transmitter Non-Inverted Data Input	
37	Tx1n	Transmitter Inverted Data Output	
38	GND	Transmitter Ground (Common with Receiver Ground)	1

Notes:

1. GND is the symbol for signal and supply (power) common for QSFP+ modules. All are common within the QSFP+ module and all module voltages are referenced to this potential unless otherwise noted. Connect these directly to the host board signal common ground plane.

^{2.} VccRx, Vcc1 and VccTx are the receiving and transmission power suppliers and shall be applied concurrently. Recommended host board power supply filtering is shown below. Vcc Rx, Vcc1 and Vcc Tx may be internally connected within the QSFP28 transceiver module in any combination. The connector pins are each rated for a maximum current of 500mA.



AOC-Q28-ER-RRR-PPP



<i>P</i>	waila	ble Platfo	rms
OEM/Designations			
A10 Networks	A1N		
Accedian	ACC		
Adtran	ADT		
Adva	ADV		ſ
Alcatel 73XX	A73		ı
Alcatel 7x50	A7x		
Alcatel TSS-100	ATS		F
Alcatel DMX	ADM		
Alcatel LambdaUnite	ALU		He
Alcatel OMNI	AOM		
Alcatel PSS 1830	A83		
Allied Telesis	ATE		
Arista	ARI		
Arista/Dell	ARD		
Arris	ARS		
Avaya/Nortel Passport	ANP		
Brocade/Foundry	BFO		
BTI	BTI		
Calix	CLX		
Check Point	CHP		
Ciena	CAN		
Ciena/Nortel OM6500	CNO		
Canoga Perkins	CGP		
Cisco	CSC		
Cisco ONS	ONS		
Coriant	CRN		
Cyan	CYN		Palo
Dasan Networks	DAN		
Dell	DLL		
Edgecore Networks	ECN		Te
Ekinops	EKS		
Enterasys	ENT		
Ericsson	ERC		
Extreme	EXT		Ubi
F5	F5		

Designations		
	Force10	F10
	Fortinet	FOR
	Fujitsu	FUJ
	Fujitsu 4100	F41
1	Fujitsu 7120	F71
ĺ	Fujitsu CDS	FCD
ĺ	Fujitsu 9500	F95
1	Gigamon	GIG
1	Hewlett Packard	HPP
1	Huawei	HWI
1	IBM	IBM
1	Infinera	INF
	lxia	IXA
	Juniper	JUN
	Mellanox	MEL
1	Meraki	MER
1	MikroTik	MTK
1	MOXA	MOX
1	MRV	MRV
	MSA	MSA
	NetApp	NTA
	NetScout	NTS
	Nokia	NOK
	Nokia 7xxx	N7x
	Occam	OCM
	Optelian	OPT
1	Palo Alto Networks	PAN
	RAD	RAD
	Raisecom	RAI
	Tejas Network	TEN
	Telco	TEL
	Tellabs	TLB
	Transmode	TSM
	Ubiquiti Networks	UBI
1	Zhone	ZHO

Cable Lengths		
Designations		
001		
002		
003		
005		
007		
010		
015		
020		
025		
030		



AOC-Q28-ER-RRR-PPP



Active Optical Cable QSFP28 to QSFP28, 100G, 1 Meter riser rated (OFNR), Universal Compatibility from L-com has same day shipment for domestic and International orders. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

L-com CAD Drawing

