

Bend Relief TRB 3-Slot Plug to Blunt Cut 1553 Cable 48" Using 124 Ohm TWC-124-2 Twinax

# 

## LC3MSA00656-48

# Configuration

Connector 1: TRB 3-Slot PlugConnector 2: Blunt Cut Genderless

• Cable Type: TWC-124-2

# **Features**

124 ohmsTwinaxialMIL-STD-1553B

Applications

- -40°C to +80°C
- · Lead Free Solder
- · Standard and Custom Lengths Available

## Applications

• MIL-STD-1553B Applications

· Data Transmission

# **Description**

L-com's LC3MSA00656-48 is a bend relief TRB 3-Slot plug to blunt cut 1553 cable 48" using 124 Ohm TWC-124-2 twinax and ships same-day. These flexible RF cable assemblies are ideal for applications where flexure is required. Our L-com TRB 3-Slot to Blunt Cut cable assembly has a plug to genderless gender configuration with 78 Ohm flexible TWC-124-2 series coax and operates to 500 MHz.

Custom versions of this TRB 3-Slot plug to TRB 3-Slot genderless cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LC3MSA00656-48 L-com Bend Relief TRB 3-Slot Plug to Blunt Cut 1553 Cable 48" Using 124 Ohm TWC-124-2 Twinax data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.

# **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		500	MHz
Capacitance		12.3 [40.35]		pF/ft [pF/m]
Operating Voltage (AC)			1,000	Vrms

Insertion Loss (Typ.)

# **Mechanical Specifications**

**Cable Assembly** 

Length\* 48 in [121.92 cm]
Weight 0.25662 lbs [116.4 g]

Cable

Cable TypeTWC-124-2Impedance124 OhmsInner Conductor TypeStrandedInner Conductor Material and PlatingCopper, Silver



# Bend Relief TRB 3-Slot Plug to Blunt Cut 1553 Cable 48" Using 124 Ohm TWC-124-2 Twinax

# 

# LC3MSA00656-48

Dielectric Type PE

Shield Layer 1 Silver Plated Copper

Jacket Material PVC, Blue

One Time Minimum Bend Radius 1.25 in [31.75 mm]

# **Connectors**

Connector 1	Connector 2
TRB 3-Slot Plug	Blunt Cut Genderless
MIL-STD-1553	
78 Ohms	
Bronze, Gold 30 micro inches	
ASTM-B-488	
Teflon	
Phosphor Bronze, Gold	
30 micro inches	
Brass, Nickel	
ASTM-B-733	
	TRB 3-Slot Plug MIL-STD-1553 78 Ohms Bronze, Gold 30 micro inches ASTM-B-488 Teflon Phosphor Bronze, Gold 30 micro inches Brass, Nickel

# **Environmental Specifications**

**Temperature** 

Operating Range -40 to +80 deg C

Compliance Certifications (see product page for current document)

# **Plotted and Other Data**

Notes:



Bend Relief TRB 3-Slot Plug to Blunt Cut 1553 Cable 48" Using 124 Ohm TWC-124-2 Twinax



# LC3MSA00656-48

# **How to Order**



Example: LC3MSA00656-12 = 12 inches long cable

LC3MSA00656-100cm = 100 cm long cable

Bend Relief TRB 3-Slot Plug to Blunt Cut 1553 Cable 48" Using 124 Ohm TWC-124-2 Twinax from L-com has same day shipment for domestic and International orders. L-com is a leading manufacturer of wired and wireless connectivity products and committed to in-stock availability and same day shipping. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

