

TRT Threaded Plug to Blunt Cut 1553 Cable 36" Using 124 Ohm TWC-124-2 Twinax

LC3MSA00677-36

Configuration

· Connector 1: TRT Threaded Plug Connector 2: Blunt Cut Genderless

• Cable Type: TWC-124-2

Features

124 ohms

MIL-STD-1553B

Twinaxial · Lead Free Solder · Standard and Custom Lengths Available

Applications · MIL-STD-1553B Applications · Data Transmission

Description

L-com's LC3MSA00677-36 is a TRT threaded plug to blunt cut 1553 cable 36" using 124 Ohm TWC-124-2 twinax and ships same-day. These flexible RF cable assemblies are ideal for applications where flexure is required. Our L-com TRT Threaded to Blunt Cut cable assembly has a plug to genderless gender configuration with 78 Ohm flexible TWC-124-2 series coax and operates to 500 MHz.

-40°C to +80°C

Custom versions of this TRT Threaded plug to TRT Threaded genderless cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LC3MSA00677-36 L-com TRT Threaded Plug to Blunt Cut 1553 Cable 36" Using 124 Ohm TWC-124-2 Twinax data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		500	MHz
Capacitance		12.3 [40.35]		pF/ft [pF/m]
Operating Voltage (AC)			1,000	Vrms
Operating Voltage (AC)			1,000	Vrn

Insertion Loss (Typ.)

Mechanical Specifications

Cable Assembly

Length* 36 in [914.4 mm] Weight 0.242 lbs [109.77 g]

Cable

TWC-124-2 Cable Type 124 Ohms Impedance Inner Conductor Type Stranded Inner Conductor Material and Plating Copper, Silver

LC3MSA00677-36 REV 1 | © 2020 Infinite Electronics, Inc. L-com is a registered trademark of Infinite Electronics, Inc.



TRT Threaded Plug to Blunt Cut 1553 Cable 36" Using 124 Ohm TWC-124-2 Twinax



LC3MSA00677-36

Dielectric Type PE

Shield Layer 1 Silver Plated Copper

Jacket Material PVC, Blue

One Time Minimum Bend Radius 1.25 in [31.75 mm]

Connectors

Connector 1	Connector 2
TRT Threaded Plug	Blunt Cut Genderless
MIL-STD-1553	
78 Ohms	
Bronze, Gold 30 micro inches	
ASTM-B-488	
Teflon	
Phosphor Bronze, Gold	
30 micro inches	
Brass, Nickel	
ASTM-B-733	
	TRT Threaded Plug MIL-STD-1553 78 Ohms Bronze, Gold 30 micro inches ASTM-B-488 Teflon Phosphor Bronze, Gold 30 micro inches Brass, Nickel

Environmental Specifications

Temperature

Operating Range -40 to +80 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:



TRT Threaded Plug to Blunt Cut 1553 Cable 36" Using 124 Ohm TWC-124-2 Twinax



LC3MSA00677-36

How to Order



Example: LC3MSA00677-12 = 12 inches long cable

LC3MSA00677-100cm = 100 cm long cable

TRT Threaded Plug to Blunt Cut 1553 Cable 36" Using 124 Ohm TWC-124-2 Twinax from L-com has same day shipment for domestic and International orders. L-com is a leading manufacturer of wired and wireless connectivity products and committed to in-stock availability and same day shipping. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

