

# 144/430 MHz, Gooseneck Antenna, SMA Female Connector



# LCANOM1155

#### **Features**

- 144/430 MHz Operating Frequency
- · Flexible Gooseneck
- · SMA Female Connector

#### **Applications**

- · Unmanned Vehicles
- · Manpack Radio Systems
- Secure Communications

- 1.5:1 VSWR
- · 10 Watt Max Input Power
- · Typical 3 dBi Gain
- · Surveillance Systems
- · Mobile Systems

### **Description**

The LCANOM1155 from L-com is an omnidirectional gooseneck antenna that features a flexible gooseneck mounting base. This flexible antenna can be bent and repositioned at any angle, allowing users to optimize signal reception and transmission in any environment. Our dual-band gooseneck antenna with vertical polarization can operate at frequencies ranging from 144 to 430 MHz.

L-com's LCANOM1155 gooseneck antenna has an impedance of 50 Ohms and a maximum input power of 10 Watts. This omnidirectional antenna is designed to withstand temperatures ranging from -40 to 80 degrees C. Our vertical polarized antenna has an overall length of 12.4 inches, a width of 1.5 inches, and a weight of 0.33 lbs. This gooseneck antenna is lightweight and compact, making it easy to transport and deploy in the field.

This vertically polarized antenna has a maximum input VSWR of 1.5:1. Our dual-band gooseneck antenna with an SMA female connector has a band 1 gain of 3.5 dBi and a band 2 gain of 5.5 dBi. This LCANOM1155 antenna comes with a black TPE radome that offers a protective covering without compromising the antenna system's performance.

## Configuration

Design Band Type Radiation Pattern Polarization Connector Type Gooseneck Dual

Omni Directional

Vertical SMA Female

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	144		430	MHz
Input VSWR			1.5:1	
Impedance		50		Ohms
Input Power			10	Watts

#### Specifications by Band

Description	Band 1	Band 2	Band 3	Band 4	Band 5	Units
Center Frequency	144	430				MHz
Gain	3.5	5.5				dBi



# 144/430 MHz, Gooseneck Antenna, SMA Female Connector



## LCANOM1155

#### **Mechanical Specifications**

Radome Material TPE

Size

 Length
 12.4 in [314.96 mm]

 Width
 1.5 in [38.1 mm]

 Height
 1.5 in [38.1 mm]

 Weight
 0.331 lbs [150.14 g]

### **Environmental Specifications**

**Temperature** 

Operating Range -40 to +80 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

**Typical Radiation Pattern** 

#### **Appendix**

Electrical Downtilt: Angle in the antenna's elevation pattern in which the maximum gain occurs.

Gain: Antenna's average gain.

Front to Back Ratio @ 180°±30°: Average difference between the antenna's maximum gain and the maximum gain in the antenna's back lobe over ±30° angles.

Cross-polarization Ratio (dB): Typical difference between the co-polarization and cross-polarization gain across the sector's 3 dB Beam Width.

Dedicated to serving the needs of the Wireless Internet Service Provider (WISP) market, KP Performance Antennas offers purpose built products that reliably perform in the field. KP Performance Antennas product line consists of Yagi, Grid, Omni, Dish and other style antennas that operate in the 900 MHz, 2.4 GHz, 3 GHz, and 5 GHz frequencies.

144/430 MHz, Gooseneck Antenna, SMA Female Connector from L-com has same day shipment for domestic and International orders. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

URL: https://www.l-com.com/144-430-mhz-gooseneck-antenna-sma-female-connector-lcanom1155-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

