

30 dB Fixed Attenuator N Male (Plug) to N Female (Jack) DC to 12 GHz Rated to 2 Watts, Brass Body, 1.35:1 VSWR



LCAT7468-30

RF Fixed Attenuators Technical Data Sheet

Features

- · DC to 12 GHz Frequency Range
- · N Connectorized Design
- Attenuation 30 dB ±5 dB

Applications

- Instrumentation
- · Precision Measurements
- · Prototyping and Characterization

- Max Power 2 Watts (CW)
- Max VSWR of 1.35:1
- · Production Systems
- WIFI 6E
- · 5G Cellular bands

Description

L-com carries a wide range of fixed attenuators with a broad selection of attenuation levels, frequency ranges, and power dissipation ranges. RF microwave attenuators (also known as RF pads) lower the amplitude of a signal (attenuate) a known amount and can be used in a wide variety of applications. These attenuator pads are used when a signal needs to be reduced to protect measurement equipment or other circuitry, to extend the range of power meters and amplifiers, and to impedance match circuits by reducing the VSWR seen by adjacent components. RF attenuators can prevent signal overload in amplifiers, receivers and detectors, adjusting the signal level to a range that is optimal.

Few RF components are as commonly used as fixed coaxial attenuators, and L-com carries one of the largest in-stock varieties and ships them same day. The 30 dB Fixed Attenuator LCAT7468-30 is rated to and operates from DC to 12 GHz. The versatile coaxial package uses N female to N male connectors.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		12	GHz
Impedance		50		Ohms
Nominal Attenuation		30		dB
VSWR			1.35:1	
Input Power, CW			2	Watts

Specifications by Frequency

F1	F2	F3	F4	F5	Units
DC to 2	2 to 5	5 to 10	10 to 12		GHz
1.15:1	1.25:1	1.35:1	1.35:1		
Typ0.5	1.5	4	5		dB
	DC to 2	DC to 2 2 to 5 1.15:1 1.25:1	DC to 2 2 to 5 5 to 10 1.15:1 1.25:1 1.35:1	DC to 2 2 to 5 5 to 10 10 to 12 1.15:1 1.25:1 1.35:1 1.35:1	DC to 2 2 to 5 5 to 10 10 to 12 1.15:1 1.25:1 1.35:1 1.35:1

Mechanical Specifications

Size

 Length
 2.1 in [53.34 mm]

 Width/Diameter
 0.827 in [21.01 mm]

 Height
 0.827 in [21.01 mm]

 Weight
 0.08 lbs [36.29 g]

 Body Material and Plating
 Brass, Tri-Metal

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 30 dB Fixed Attenuator N Male (Plug) to N Female (Jack) DC to 12 GHz Rated to 2 Watts, Brass Body, 1.35:1 VSWR LCAT7468-30



30 dB Fixed Attenuator N Male (Plug) to N Female (Jack) DC to 12 GHz Rated to 2 Watts, Brass Body, 1.35:1 VSWR



LCAT7468-30

Configuration

Design Package Style Fixed, Bi-Directional Conectorized

Connectors

Description	Connector 1	Connector 2	
Туре	N Female	N Male	
Contact Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold	
Dielectric Type	Teflon	Teflon	
Body Material and Plating	Brass, Tri-Metal	Brass, Tri-Metal	

Environmental Specifications

Compliance Certifications

Plotted and Other Data

Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part

described herein for any particular purpose, and L-com does not assume any liability arising out of the use of any part or documentation.

LCAT7468-30 CAD Drawing30 dB Fixed Attenuator N Male (Plug) to N Female (Jack) DC to 12 GHz Rated to 2 Watts, Brass Body, 1.35:1 VSWR

