



#### LCCA30362-FT2

## Configuration

- · Connector 1: SMA Male
- Connector 2: SMA Female Bulkhead
- Cable Type: RG223

#### **Features**

- · Max Frequency 12.4 GHz
- 66% Phase Velocity

## **Applications**

General Purpose

- · Double Shielded
- PVC Jacket

· Laboratory Use



## **Description**

L-com's LCCA30362-FT2 is a SMA male to SMA female bulkhead cable assembly using RG223 coax, 2 FT and ships same-day. The RG223 coax of this SMA cable uses the PE dielectric with a VoP of 66%. These flexible RF cable assemblies are ideal for applications where flexure is required. Our L-com SMA to SMA cable assembly has a male to female gender configuration with flexible RG223 series coax and operates to 12.4 GHz. The double shield of this SMA cable is layered by silver plated copper braid over silver plated copper braid. L-com's RF cable assembly with SMA bulkhead interface enables system designers to have external connections on their product enclosures or to be used for other rack mount and panel mount applications.

Custom versions of this SMA male to SMA female cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LCCA30362-FT2 L-com SMA Male to SMA Female Bulkhead Cable Assembly using RG223 Coax, 2 FT data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.





## LCCA30362-FT2

## **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		12.4	GHz
VSWR			1.5:1	
Velocity of Propagation		66		%
Capacitance		30.8 [101.05]		pF/ft [pF/m]
Operating Voltage (AC)			500	Vrms

## **Specifications by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.5	1	2.5	5	11	GHz
Insertion Loss (Typ.)	0.4	0.48	0.6	0.88	1.3	dB

## **Electrical Specification Notes:**

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in the assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB per connector.

## **Mechanical Specifications**

#### **Cable Assembly**

 Length
 24 in [609.6 mm]

 Diameter
 0.315 in [8 mm]

 Weight
 0.066 lbs [29.94 g]

#### Cable

Cable Type RG223
Impedance 50 Ohms
Inner Conductor Type Solid
Inner Conductor Material and Plating Copper, Silver
Dielectric Type PE
Number of Shields 2

Shield Layer 1 Silver Plated Copper Braid
Shield Layer 2 Silver Plated Copper Braid
Jacket Material PVC, Black

Jacket Diameter 0.21 in [5.33 mm]

One Time Minimum Bend Radius 0.984 in [24.99 mm]





# LCCA30362-FT2

## **Connectors**

Description	Connector 1	Connector 2		
Туре	SMA Male	SMA Female Bulkhead		
Specification	MIL-STD-348A	MIL-STD-348A		
Impedance	50 Ohms	50 Ohms		
Contact Material and Plating	Brass, Gold	Beryllium Copper, Gold		
Contact Plating Specification	50μ in. minimum	50μ in. minimum		
Dielectric Type	Teflon	Teflon		
Body Material and Plating	Brass, Nickel	Brass, Nickel		
Body Plating Specification	100μ in. minimum	100μ in. minimum		
Hex Size	5/16 in			
Torque	5 in-lbs 0.57 Nm			

Compliance Certifications (see product page for current document)

## **Plotted and Other Data**


Notes:





#### LCCA30362-FT2

#### **How to Order**



Example: LCCA30362-12 = 12 inches long cable LCCA30362-100cm = 100 cm long cable

SMA Male to SMA Female Bulkhead Cable Assembly using RG223 Coax, 2 FT from L-com has same day shipment for domestic and International orders. L-com is a leading manufacturer of wired and wireless connectivity products and committed to in-stock availability and same day shipping. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

## **L-com CAD Drawing**

