



#### LCCA30539-FT1.5

## Configuration

Connector 1: SMA MaleConnector 2: N MaleCable Type: LC085TB

#### **Features**

- Max Frequency 11 GHz
- Shielding Effectivity > 100dB
- PTFE Dielectric with 69.5% VoP

### **Applications**

- General Purpose
- · Laboratory Use

- Hand Formable
- Tin Filled Copper Composite Braid Outer Conductor
- · System Interconnect



## **Description**

L-com's LCCA30539-FT1.5 is a SMA male to N male cable assembly using LC085TB coax, 1.5 FT and ships same-day. The LC085TB coax of this SMA cable uses the PTFE dielectric with a VoP of 69.5%. These formable RF cable assemblies are a great alternative to expensive semi-rigid assemblies because they can be hand formed to fit specific designs. Our L-com SMA to N cable assembly has a male to male gender configuration with formable LC085TB series coax and operates to 11 GHz. The outer conductor can be easily formed by hand and has an overall diameter of 0.085 inches.

Custom versions of this SMA male to SMA male cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LCCA30539-FT1.5 L-com SMA Male to N Male Cable Assembly using LC085TB Coax, 1.5 FT data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.





## LCCA30539-FT1.5

## **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		11	GHz
VSWR			1.45:1	
Velocity of Propagation		69.5		%
Capacitance		29 [95.14]		pF/ft [pF/m]
		. ,		, ,

# **Specifications by Frequency**

Description	F1	F2	F3	F4	F5	Units	
Frequency	0.5	1	2.5	5	11	GHz	
Insertion Loss (Typ.)	0.43	0.55	0.73	1.02	1.41	dB	

# Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB per connector.

## **Mechanical Specifications**

#### **Cable Assembly**

 Length
 18 in [457.2 mm]

 Diameter
 0.79 in [20.07 mm]

 Weight
 0.0633 lbs [28.71 g]

#### Cable

Cable TypeLC085TBImpedance50 OhmsInner Conductor TypeSolid

Inner Conductor Material and Plating Copper Clad Steel, Silver Dielectric Type PTFE

Number of Shields

Shield Layer 1 Tinned Copper Braid
Outer Conductor Diameter 0.085 in [2.16 mm]





# LCCA30539-FT1.5

## **Connectors**

Connector 1	Connector 2	
SMA Male	N Male	
50 Ohms	50 Ohms	
Brass, Gold over Nickel	Brass, Gold	
PTFE	PTFE	
Brass, Gold over Nickel	Brass, Nickel	
Passivated Stainless Steel	Brass, Nickel	
5/16 in.		
8 in-lbs 0.9 Nm		
	SMA Male 50 Ohms Brass, Gold over Nickel PTFE Brass, Gold over Nickel Passivated Stainless Steel 5/16 in.	

Compliance Certifications (see product page for current document)

**Plotted and Other Data** 

Notes:





#### LCCA30539-FT1.5

#### **How to Order**



Example: LCCA30539-12 = 12 inches long cable LCCA30539-100cm = 100 cm long cable

SMA Male to N Male Cable Assembly using LC085TB Coax, 1.5 FT from L-com has same day shipment for domestic and International orders. L-com is a leading manufacturer of wired and wireless connectivity products and committed to in-stock availability and same day shipping. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

# **L-com CAD Drawing**

