

SMA Female to N Male Cable Assembly using LC085TB Coax, 5 FT



LCCA30547-FT5

Configuration

Connector 1: SMA FemaleConnector 2: N MaleCable Type: LC085TB

Features

- Max Frequency 11 GHz
- Shielding Effectivity > 100dB
- PTFE Dielectric with 69.5% VoP

Applications

- General Purpose
- · Laboratory Use

- Hand Formable
- Tin Filled Copper Composite Braid Outer Conductor
- · System Interconnect



Description

L-com's LCCA30547-FT5 is a SMA female to N male cable assembly using LC085TB coax, 5 FT and ships same-day. The LC085TB coax of this SMA cable uses the PTFE dielectric with a VoP of 69.5%. These formable RF cable assemblies are a great alternative to expensive semi-rigid assemblies because they can be hand formed to fit specific designs. Our L-com SMA to N cable assembly has a female to male gender configuration with formable LC085TB series coax and operates to 11 GHz. The outer conductor can be easily formed by hand and has an overall diameter of inches.

Custom versions of this SMA female to SMA male cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LCCA30547-FT5 L-com SMA Female to N Male Cable Assembly using LC085TB Coax, 5 FT data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units	
Frequency Range	DC		11	GHz	



SMA Female to N Male Cable Assembly using LC085TB Coax, 5 FT



LCCA30547-FT5

VSWR		1.45:1
Velocity of Propagation	69.5	%
Capacitance	29 [95.14]	pF/ft [pF/m]

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units	
Frequency	0.5	1	2.5	5	11	GHz	
Insertion Loss (Typ.)	0.95	1.35	1.95	2.95	4.45	dB	

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB per connector.

Mechanical Specifications

Cable Assembly

 Length
 60 in [152.4 cm]

 Diameter
 0.79 in [20.07 mm]

 Weight
 0.0699 lbs [31.71 g]

Cable

Cable TypeLC085TBImpedance50 OhmsInner Conductor TypeSolidInner Conductor Material and PlatingCopper Clad Steel, SilverDielectric TypePTFENumber of Shields1Shield Layer 1Tinned Copper Braid

Connectors

Description	Connector 1	Connector 2
Туре	SMA Female	N Male
Impedance	50 Ohms	50 Ohms
Contact Material and Plating	Beryllium Copper, Gold	Brass, Gold
Dielectric Type	PTFE	PTFE
Body Material and Plating	Brass, Gold	Brass, Nickel
Coupling Nut Material and Plating		Brass, Nickel



SMA Female to N Male Cable Assembly using LC085TB Coax, 5 FT



LCCA30547-FT5

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:

LCCA30547 - xx uu

Unit of Measure:
cm = Centimeters

chlank> = Inches
Length
Base Number

Example: LCCA30547-12 = 12 inches long cable LCCA30547-100cm = 100 cm long cable

SMA Female to N Male Cable Assembly using LC085TB Coax, 5 FT from L-com has same day shipment for domestic and International orders. L-com is a leading manufacturer of wired and wireless connectivity products and committed to in-stock availability and same day shipping. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

L-com CAD Drawing

