

LCCA9965

Configuration

Connector 1: SMA Male
Connector 2: TNC Male
Cable Type: LMR-400-UF
Coax Flex Type: Flexible

Description

L-com's LCCA9965 is a low loss SMA male to TNC male cable assembly using LMR-400-UF coax with Times Microwave components with heatshrink and ships same-day. The LMR-400-UF coax of this SMA cable uses the PE (F) dielectric with a VoP of 85%, resulting in very low insertion loss compared to solid dielectrics. These flexible RF cable assemblies are ideal for applications where flexure is required. Our L-com SMA to TNC cable assembly has a male to male gender configuration with flexible LMR-400-UF series coax and operates to 5.8 GHz. The double shield of this SMA cable is layered by tinned copper braid over aluminum tape providing shielding effectiveness greater than 90dB.

Custom versions of this SMA male to SMA male cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LCCA9965 L-com Low Loss SMA Male to TNC Male Cable Assembly using LMR-400-UF Coax With Times Microwave Components with HeatShrink data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		5.8	GHz
VSWR			1.5:1	
Velocity of Propagation		85		%
RF Shielding	90			dB
Group Delay		1.2 [3.94]		ns/ft [ns/m]
Capacitance		23.9 [78.41]		pF/ft [pF/m]
Inductance		0.06 [0.2]		uH/ft [uH/m]
DC Resistance Inner Conductor		1.07 [3.51]		Ohms/1000ft [Ohms/Km]
DC Resistance Outer Conductor		1.65 [5.41]		Ohms/1000ft [Ohms/Km]
Dielectric Withstanding Voltage (DC)			2,500	Vdc
Jacket Spark			8,000	Vrms
Input Power (Peak)			16	KWatts

Specifications by Frequency





LCCA9965

Part Number	Length	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
		Frequency	250	500	1000	2500	5800	MHz	
LCCA9965	Custom Lengths	Insertion Loss (Typ.)	0.023	0.034	0.049	0.081	0.13	dB/ft	
ECCA9903	Available	ilisertion Loss (Typ.)	0.08	0.12	0.17	0.27	0.43	dB/m	
LCCA9965-FT1	12 inch	Insertion Loss (Typ.)	0.23	0.24	0.25	0.29	0.33	dB	0.229
LCCA9965-FT2	24 inch	Insertion Loss (Typ.)	0.25	0.27	0.3	0.37	0.46	dB	0.316
LCCA9965-FT3	36 inch	Insertion Loss (Typ.)	0.27	0.31	0.35	0.45	0.59	dB	0.403
LCCA9965-FT5	60 inch	Insertion Loss (Typ.)	0.32	0.37	0.45	0.61	0.85	dB	0.577
LCCA9965-FT25	300 inch	Insertion Loss (Typ.)	0.78	1.05	1.43	2.23	3.45	dB	2.317

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

Loss due to Connector 1: 0.1 dB Loss due to Connector 2: 0.1 dB Base Weight: 0.229 pounds Additional Weight per Inch: 0.00725 pounds

Mechanical Specifications

Cable Assembly

Width/Diameter 0.5 in [12.7 mm] Weight 0.229 lbs [103.87 g]

Cable

Cable Type Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type

Number of Shields Shield Layer 1 Shield Layer 2 Jacket Material

Jacket Diameter

One Time Minimum Bend Radius

Repeated Minimum Bend Radius **Bending Moment**

Flat Plate Crush Tensile Strength

LMR-400-UF Stranded Copper PE(F)

Aluminum Tape Tinned Copper Braid

TPE

0.405 in [10.29 mm] 1 in [25.4 mm] 4 in [101.6 mm] 0.38 lbs-ft [0.52 N-m] 20 lbs/in [0.36 Kg/mm] 160 lbs [72.57 Kg]





LCCA9965

Connectors

Description	Connector 1	Connector 2
Туре	SMA Male	TNC Male
Configuration	Straight	Straight
Mating Cycles		500
Contact Material and Plating	Brass, Gold	Brass, Gold
Contact Plating Specification	50μin. minimum	
Dielectric Type	Teflon	
Body Material and Plating	Brass, Tri-Metal	Brass, Tri-Metal
Coupling Nut Material and Plating	Brass, Tri-Metal	Brass, Tri-Metal

Environmental Specifications

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Values at 25°C, sea level.





LCCA9965

Typical Performance Data

How to Order

Part Number Configuration:

LCCA9965 - xx uu

Unit of Measure:
cm = Centimeters

Length
Base Number

Example: LCCA9965-12 = 12 inches long cable

LCCA9965-100cm = 100 cm long cable

Low Loss SMA Male to TNC Male Cable Assembly using LMR-400-UF Coax With Times Microwave Components with HeatShrink from L-com has same day shipment for domestic and International orders. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

URL: https://www.l-com.com/sma-male-tnc-male-cable-assembly-invalid-lcca9965-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

LCCA9965 CAD Drawing

Low Loss SMA Male to TNC Male Cable Assembly using LMR-400-UF Coax With Times Microwave Components with HeatShrink

